

CC800v2 IP 话务盒快速操作指南



LEDs

● 表 1 线路键灯

LED 灯状态	描述
红色闪烁	对应线路有来电正在呼入
红色常亮	对应线路摘机且正在进入正常通话状态

● 表 2 状态灯

LED 灯状态	描述
红色闪烁	某线路有来电正在呼入及线路被保持
红色常亮	某线路摘机且正在进入正常通话状态

● 表 3 免提键

LED 灯状态	描述
红色常亮	摘机或通话状态

● 表 3 其他

LED 灯状态	描述
红色常亮	对应功能正启用

安装指引

安装耳机架，如图 1 和图 2 所示：

- 图 1：话务盒翻转，背部卡槽为耳机支架安装孔，对准后向里轻轻一推即可拴紧耳机支架。
- 图 2：耳机支架可放置耳机，方便使用。




图 1



图 2

注：耳机和耳机架非标准配件。

话机接口功能，如图 3 和图 4 所示：

- 图 3：耳机 RJ11 接口；SUPERVISOR 监听接口。
- 图 4：PC 口接电脑，LAN 口接外网，电源口接电源 (DC5V)，USB 电源口接 USB，3.5mm 耳机口接耳机。




图 3




图 4

网络配置

- 按话机 LCD 界面上的“菜单”软键（按向下软按键或者数字 2\4\6\8 键操作）=> 系统设置=> 高级设置=> 输入高级设置密码（默认为空）=> 网络=>本地网口设置=>网络类型=>按“进入”键进入修改后“保存”。

网络选项：静态 IP、拨号 PPPoE、DHCP 自动获取

选择静态 IP 后按导航键下，看到 IP 地址设置，可对 IP 及网关等网络信息进行设置，其中“.” 请用键“*”输入，修改完后“保存”。选择 PPPoE 输入账号和密码后按保存。

选择 DHCP 不用设置 IP。

注：修改了网络参数，需要重启才能使其生效，请选择重启；数字 2\4\6\8 键复用为导航键上\左\右\下。

可编程按键

- 登陆话机网页话机设置>高级>功能键，可对 L1\L2\AUTO ANS\HOLD\RD 键进行可编程功能修改，根据功能所需可从新定义为快速拨号\快速拨号前缀\DTMF 二次拨号\Paging\Call Park\Intercom\Pick up\BLA。

注册账号

- 按话机 LCD 界面上的菜单软键（按“向下”软按键或者数字“8”键）=> 系统设置=> 高级设置=> 输入高级设置密码（默认为空=> Sip=> 账号 SIP 设置 =>账号 1，之后分别配置以下参数：启用、账号类型、账号、密码、主 SIP 域名
- 主 SIP 域名：输入 SIP 服务器 IP（“.” 请用键*输入，注意 IP 话机与 SIP 服务器间网络必须可达），之后按“确定”，再按下“保存”软键，即可完成 SIP 账户的添加。

发起呼叫

您可以按下耳麦键来进行一个呼叫。

- IP 直呼：摘机或者待机状态下，直接拨 IP 地址呼叫另一台 IP 话机
- 直接呼叫：直接拨打号码，然后按#键或按发出软键；
- 重拨：按 RD 功能按键以拨打最近一个拨出的号码；
- 从呼叫记录进行呼叫：按菜单键，选择“呼叫记录”，再选择“未接来电”、“已接来电”或“已拨电话”列表来选择一个号码，按“进入”软键再按“呼叫”菜单进行呼叫。

配件清单

列表	数量
话机	1
网线	1
USB 线	1
快速操作指南	1

*更多的详细内容以及话机配置信息请参考本话机的用户手册。您也可以通过访问话机的 Web 页面来进行更详细的参数配置，在浏览器中输入 IP 话机的地址，输入话机的用户名、密码（默认均为 root），即可进入了 IP 话机的网页配置界面。

escene

广州市亿景通信技术有限公司

地址：广州市天河区东圃镇黄村路 51 号粤安工业园 C 栋 4 楼

网址：<http://www.escene.cn>

客户服务：400 090 5818

CC800v2 IP Phone Quick Guide



LEDs

Table 1 Line 1\2

LED Status	Description
Red, flashing	There is an incoming call.
Red, steady	Pick up and enter normal call.

Table 2 Light-strip

LED Status	Description
Red, flashing	There is an incoming call or be Hold.
Red, steady	Hook-off. or enter a usual conversation

Table 2 Headset

LED Status	Description
Red, steady	Pick up and enter normal call.

Table 3 Others

LED Status	Description
Red, steady	The corresponding function is enabled.

Installation Guide

Bracket installation and usage are as following pictures:

Figure 1: Push the bracket down and it can match the bottom card slot.

Figure 2: It's convenient to hang headset onto the bracket.

Figure 3~4: Some of the interfaces, e.g: Supervisor interface\Headset interface\3.5mm headset interface\PC port\ Internet port\Power port\USB power supply.




Figure 1




Figure 2

Note: The bracket and headset are non-standard parts.




Figure3




Figure4

Network Setting

- Press the menu soft key on the phone **MENU=> System setting=> Advanced setting=>** Enter **Advanced Password** (Empty by default) => **Network =>LAN Port** click **ENTER**

Type has the following options : **STATIC\PPPoE\DHCP**

Choose **STATIC** press Navigation key - to the next, see the IP address settings, the IP and gateway settings and other related network information, including "." Use the key "*" entry.

Select **PPPoE** username and password to register.

Select **DHCP** needn't to setting IP.

NOTE: when network configuration has been changed, must reboot to take effect, please select reboot.; 2\4\6\8 are navigation keys when operating menu.

DSS Keys

- Login the phone website>Phone Settings> Advanced>Function(DSS) keys, you can set the Function(DSS) Keys as Speed Dial\Speed Dial Prefix\DTMF\Paging\Call Park\Intercom\Pickup\BLA.

Registered Account

- On the idle status, you can start to configure account by pressing **MENU** soft key => **System Setting => Advanced Setting=>type Advanced password** (it is idle by default) => **SIP Account**, the main parameters for 2 SIP accounts are needed to be set as follow:

Enable Account: Select Enable

Account: Type your SIP account

Authen User: The authentication with the account

User Pwd : Type your SIP password

SIP Server : Type the SIP server IP address (you can type "." by "*" key, you must confirm the connection between the phone and SIP server), And then select Submit changes and press OK to submit the changes.

Placing a Call

You can press **Headset/Speaker** button to place a call.

- Dial directly:** Dial number directly, then press # button or Send soft-key (it will call from the first available line);
- Redial:** Press **Redial** button/soft-key to dial the latest number;
- Dial from Call history:** Press **Menu** button, select "Call history" and select one of "Missed calls", "Received calls" and "Dialed numbers" lists to dial by pressing **Dial** soft-key.

You can quickly use these functions by pressing corresponding Navigation-buttons [2\4\6\8]. For example, **Left** button : "Received Calls" list ; **Right** button : "Dialed Numbers" list ; **Down** button : "Missed Calls" list . **UP** button :"tone volume" ;

Summary

List	Quantity
Phone	1
Ethernet Cable	1
USB Cable	1
Quick Operator Guide	1

*This document introduces normal function operation of IP phones only. For details (operation and configuration), refer to User Manual. And set details on the web page of phone. In the browser, enter the IP phone's address, enter the phone's user name and password (the default are root), enter the IP phone's web configuration interface.



ESCENE COMMUNICATION CO.,LTD.

Web: <http://www.escene.cn/en>

Address: Floor 4 Building C YueAn Industrial Park No.51 Huangcun Road Tianhe District Guangzhou China